

# SA30

Class G Intelligent Integrated Amplifier

ARCAM  
by HARMAN



## Features

- Class G amplification for impeccable sound and efficiency
- 120W of power per channel into 8Ω, 220W into 4Ω
- 5 analogue inputs including switchable MM/MC PHONO input
- 4 digital inputs
- 1 ARC input
- GoogleCast, Airplay 2, uPnP Streamer
- Roon endpoint
- MQA supported
- 3 Dirac EQ profiles (input assignable)
- 32-bit DAC, Sabre ESS9038K2M
- Full I/P control including Control4 and Crestron
- Total harmonic distortion + noise = 0.002%

## Specifications

Frequency Response	20Hz – 20kHz ± 1dB
Nominal Sensitivity	1V
Input Impedance	10kΩ
Power output both channels driven	120W into 8Ω, 220W into 4Ω
Maximum Input	6Vrms
Signal/Noise ratio (A-wtd) 50W, ref. 1V input	120dB
Mains Voltage	110-120V or 220-240V, 50-60Hz
Maximum Power Consumption	800W
Dimensions W x H x D (including feet, control knob and speaker terminals)	433x100x323mm
Weight	12kg
Packaged Weight	14kg